

PRODUCT-DETAILS

# MO325-2.5

## MO325-2.5 Manual Motor Starter Magnetic Only 2.5 A



### General Information

Extended Product Type	MO325-2.5
Product ID	1SAM160000R1007
EAN	4013614302039
Catalog Description	MO325-2.5 Manual Motor Starter Magnetic Only 2.5 A

Long Description	<p>The MO325-2.5 manual motor starter magnetic only is a 54 mm width device with a rated operational current of <math>I_e = 2.50</math> A. This device is used to manually switch on and off motors and to protect them reliably and without the need for a fuse from short-circuits. The manual motor starter magnetic only offers a rated service short-circuit breaking capacity <math>I_{cs} = 100</math> kA at 400 VAC. Further features are the build-in disconnect function, trip-free mechanism and a rotary handle with a clear switch position indication. The manual motor starter magnetic only is suitable for three- and single-phase applications. Auxiliary contacts, signalling contacts, undervoltage releases, shunt trips, 3-phase bus bars, power in-feed blocks are available as accessory.</p>
------------------	---

### Ordering

Minimum Order Quantity	1 piece
Customs Tariff Number	85362010
Replacement Product ID (NEW)	1SAM360000R1007

### Popular Downloads

Data Sheet, Technical	2CDC131047D0201
-----------------------	-----------------

## Information

Instructions and Manuals	2CDC131089M6801
--------------------------	-----------------

## Dimensions

Product Net Width	54 mm
Product Net Height	87.5 mm
Product Net Depth / Length	75.5 mm
Product Net Weight	0.34 kg

## Technical

Rated Service Short-Circuit Breaking Capacity ( $I_{cs}$ )	(230 V AC) 100 kA (400 V AC) 100 kA (440 V AC) 100 kA (500 V AC) 100 kA (690 V AC) 40 kA
Rated Ultimate Short-Circuit Breaking Capacity ( $I_{cu}$ )	(230 V AC) 100 kA (400 V AC) 100 kA (440 V AC) 100 kA (500 V AC) 100 kA (690 V AC) 40 kA
Rated Instantaneous Short-Circuit Current Setting ( $I_i$ )	27.5 A
Setting Range	None
Rated Operational Power AC-3 ( $P_e$ )	(400 V) Three Phase 0.75 kW
Rated Operational Voltage	Main Circuit 690 V AC Main Circuit 440 V DC
Rated Operational Current ( $I_e$ )	2.5 A
Rated Operational Current AC-3 ( $I_e$ )	2.5 A
Rated Frequency (f)	Main Circuit 50 Hz Main Circuit 60 Hz
Rated Impulse Withstand Voltage ( $U_{imp}$ )	Main Circuit 6 kV
Rated Insulation Voltage ( $U_i$ )	690 V
Power Loss	at Rated Operating Conditions per Pole 2.1 W
Number of Poles	3
Number of Auxiliary Contacts NC	0
Number of Auxiliary Contacts NO	2
Conventional Free-air Thermal Current ( $I_{th}$ )	Main Circuit 2.5 A
Degree of Protection	Housing IP20 Main Circuit Terminals IP20
Pollution Degree	3
Electrical Durability	50000 cycle
Mechanical Durability	100000 cycle
Terminal Type	Screw Terminals
Connecting Capacity Main Circuit	Flexible with Ferrule 1/2x 0.75 ... 4 mm <sup>2</sup> Flexible with Insulated Ferrule 1/2x 0.75 ... 4 mm <sup>2</sup> Flexible 1/2x 1 ... 6 mm <sup>2</sup> Rigid 1/2x 1 ... 6 mm <sup>2</sup>

Connecting Capacity Auxiliary Circuit	Flexible with Ferrule 1/2x 0.75 ... 1.5 mm <sup>2</sup> Flexible with Insulated Ferrule 1/2x 0.75 ... 2.5 mm <sup>2</sup> Flexible 1/2x 0.75 ... 1 mm <sup>2</sup> Rigid 1/2x 1.0 ... 2.5 mm <sup>2</sup>
Tightening Torque	Auxiliary Circuit 0.8 ... 1.0 N·m Main Circuit 1.4 N·m
Wire Stripping Length	Auxiliary Circuit 8 mm Main Circuit 10 mm
Recommended Screw Driver	Pozidriv 2 M3.5
Mounting Position	1 ... 6
Mounting on DIN Rail	TH35-15 (35 x 15 mm Mounting Rail) acc. to IEC 60715 TH35-7.5 (35 x 7.5 mm Mounting Rail) acc. to IEC 60715
Actuator Type	Rotary Handle
Contact Position Indication	ON / OFF
Standards	CSA 22.2 No. 14 IEC/EN 60947-1 IEC/EN 60947-2 IEC/EN 60947-4-1 UL 508
Remarks	For overload protection of the motors, an appropriate thermal or electronic overload relays must be used

## Technical UL/CSA

Maximum Operating Voltage UL/CSA	Main Circuit 600 V AC
Horsepower Rating UL/CSA	(220 ... 240 V AC) Three Phase 0.5 Hp (440 ... 480 V AC) Three Phase 1 Hp (550 ... 600 V AC) Three Phase 1.5 Hp
Connecting Capacity Main Circuit UL/CSA	Flexible 1/2x 14-8 AWG Stranded 1/2x 14-8 AWG
Connecting Capacity Auxiliary Circuit UL/CSA	Flexible 1/2x 14-8 AWG Stranded 1/2x 14-18 AWG
Tightening Torque UL/CSA	Auxiliary Circuit 7 in·lb Main Circuit 14 in·lb
Contact Rating UL/CSA	B300 Q300

## Environmental

Ambient Air Temperature	Around the Enclosure 0 ... +40 °C Operation -25 ... +50 °C Storage -50 ... +80 °C
Ambient Air Temperature Compensation	No
Maximum Operating Altitude Permissible	2000 m
Resistance to Shock acc. to IEC 60068-2-27	11 ms Pulse 15g
Resistance to Vibrations acc. to IEC 60068-2-6	5g / 10 ... 150 Hz
RoHS Status	Following EU Directive 2011/65/EU and Amendment 2015/863 July 22, 2019

## Certificates and Declarations

CB Certificate	1SAA918000-2003
CQC Certificate	CQC2017010307033534
cUL Certificate	cUL_E137861

cULus Certificate	E137861
Declaration of Conformity - CCC	2020980307003580
Declaration of Conformity - CE	1SAD101100-3413
Declaration of Conformity - UKCA	1SAD201100-3413
DNV Certificate	1SAA918000-0306
GL Certificate	1SAA918000-0403
LR Certificate	1SAA918000-0504
RINA Certificate	1SAA918000-0804
RMRS Certificate	1SAA918000-0704
UL Certificate	UL_E137861

## Container Information

Package Level 1 Units	box 1 piece
Package Level 1 Width	92 mm
Package Level 1 Depth / Length	58 mm
Package Level 1 Height	78 mm
Package Level 1 Gross Weight	0.37 kg
Package Level 1 EAN	4013614302039
Package Level 2 Units	carton 24 piece
Package Level 2 Width	280 mm
Package Level 2 Depth / Length	395 mm
Package Level 2 Height	210 mm
Package Level 2 Gross Weight	8.9 kg
Package Level 2 EAN	4013614494994

## Classifications

Object Classification Code	F
ETIM 4	EC000074 - Motor protective circuit-breaker
ETIM 5	EC000074 - Motor protective circuit-breaker
ETIM 6	EC000074 - Motor protection circuit-breaker
ETIM 7	EC000074 - Motor protection circuit-breaker
ETIM 8	EC000074 - Motor protection circuit-breaker
eClass	V11.0 : 27370401
UNSPSC	39121521
IDEA Granular Category Code (IGCC)	4731 >> Manual Starters

## Categories

Low Voltage Products and Systems → Circuit Breakers → Manual Motor Starters

Low Voltage Products and Systems → Control Products → Manual Motor Starters → Manual Motor Starters

